

**Partner: Biamp**  
**Model: Tesira**  
**Device Type: Digital Signal Processor**



## GENERAL INFORMATION

<b>SIMPLWINDOWS NAME:</b>	Biamp Tesira Preset Control v2.0
<b>CATEGORY:</b>	Mixer
<b>VERSION:</b>	2.0
<b>SUMMARY:</b>	This module controls presets recall for the Biamp Tesira.
<b>GENERAL NOTES:</b>	The Biamp Tesira allows controlling Preset by Number or Name. This module allows for both methods. The Preset_*_Name_Number parameters are used to assign the preset to recall when the Recall_Preset_* digital is pulsed. If the assigned value contains a string value from 1001 on, the Biamp Tesira Preset Control v2.0 module will send the value as a preset number. Any non-numeric value will be sent as a named preset recall.
<b>CRESTRON HARDWARE REQUIRED:</b>	3-series processor <b>only</b> (Note: use 1.X modules for 2-series processors)
<b>SETUP OF CRESTRON HARDWARE:</b>	This module requires the Biamp Tesira Command Processor IP v2.0 or the Biamp Tesira Command Processor RS232 v2.0 modules in order to operate. Please read the help files associated with these modules.
<b>VENDOR FIRMWARE:</b>	Tesira Server - 2.6.0.16 Tesira Forte - 2.6.0.16

**Partner: Biamp**  
**Model: Tesira**  
**Device Type: Digital Signal Processor**

**PARAMETER:**

<b>Preset_*_Name_Number</b>	The Biamp Tesira allows controlling Preset by Number or Name. This module allows for both methods. The Preset_*_Name_Number parameters are used to assign the preset to recall when the Recall_Preset_* digital is pulsed. If the assigned value contains a string value from 1001 on, the Biamp Tesira Preset Control v2.0 module will send the value as a preset number. Any non-numeric value will be sent as a named preset recall.
<b>Command_Processor_ID</b>	Setting to indicate the ID for the command processor that this module will register itself with.

**Partner: Biamp**  
**Model: Tesira**  
**Device Type: Digital Signal Processor**

**CONTROL:**

Recall_Preset_*	D	Pulsing this signal will send the assigned Preset_*_Name_Number as a named preset or a number preset depending on its value.
-----------------	---	------------------------------------------------------------------------------------------------------------------------------

**Partner: Biamp**  
**Model: Tesira**  
**Device Type: Digital Signal Processor**

**FEEDBACK:**

Is\_Initialized

D

Signal is high to indicate the module has successfully received all required responses from its initializing queries.

**Partner: Biamp**  
**Model: Tesira**  
**Device Type: Digital Signal Processor**

**TESTING:**

<b>OPS USED FOR TESTING:</b>	CP3: 1.501.0013
<b>SIMPL WINDOWS USED FOR TESTING:</b>	4.06.01
<b>CRES DB USED FOR TESTING:</b>	61.05.007.00
<b>DEVICE DATABASE:</b>	81.05.003.00
<b>SYMBOL LIBRARY USED FOR TESTING:</b>	1023
<b>SAMPLE PROGRAM:</b>	Biamp Tesira v2.0 IP Demo Biamp Tesira v2.0 RS232 Demo
<b>REVISION HISTORY:</b>	v2.0 – Initial Release