



Partner: QSC-Q-SYS
Model: Q-SYS Cores
Device Type: DSP

GENERAL INFORMATION

SIMPLWINDOWS NAME:	Q-SYS [Core Backup Handler] V4.0
CATEGORY:	Q-SYS V4
VERSION:	V4.0
SUMMARY:	This module is used to handle the backup/redundant control feature of a QSYS system
GENERAL NOTES:	This module is used to monitor and control the backup/redundant core of an applicable system. This module will monitor the status of just the backup core, if it sees the backup core has become the active core, it will re-register all of the named control modules to its' IP address. It can also be used to switch back to the primary core, if the problem with the QSYS system is resolved. This avoids having to reboot/restart the program.
CRESTRON HARDWARE REQUIRED:	Ethernet Card – 3-Series Only
SETUP OF CRESTRON HARDWARE:	3-Series Only
VENDOR FIRMWARE:	Unknown
VENDOR SETUP:	The QSYS design must account for a backup/redundant core.

CONTROL:

Get_Status	D	Pulse to check status of backup/redundant core. Usually tied to an oscillator symbol. Since importance will vary based on application, this will solely be at the programmer's discretion.
Redundant_Core_IP	S	IP/Host of the backup/redundant core.

FEEDBACK:

Now_Active	D	Signal used to indicate if backup/redundant core is now the active running core. When this signal goes low, it is indicating the backup/redundant core is once again "idle", at which time the original "primary" core address should be sent to the core module. ([Core_Change_IP_Address]).
New_Active_IP	S	String to attach to the core module ([Core_Change_IP_Address]). Will force the core module to reinitialize.



Partner: QSC-Q-SYS
Model: Q-SYS Cores
Device Type: DSP

TESTING:

OPS USED FOR TESTING:	v4.001.1012
SIMPL WINDOWS USED FOR TESTING:	4.07.03
DEVICE DB USED FOR TESTING:	85.05.003.00
CRES DB USED FOR TESTING:	63.05.007.0
SYMBOL LIBRARY USED FOR TESTING:	1035
SAMPLE PROGRAM:	Q-SYS V4.0 Demo Program
REVISION HISTORY:	V4.0 – Completely Revamped Module Set.