



Partner: Sony

Model: 2014 Bravia TV

Device Type: TV



GENERAL INFORMATION				
SIMPLWINDOWS NAME:	Sony 2014 Bravia TV v1.0			
CATEGORY:	TV/Video Projector			
VERSION:	1.0			
SUMMARY:	This module provides TCP/IP control and feedback for Sony 2014 Bravia TVs.			
GENERAL NOTES:	This module provides TCP/IP control of the Sony 2014 Bravia TVs. It also provides feedback. It was tested with model KDL-40W600B. It uses the Simple IP Control protocol. NOTE: Not all functions and inputs are available on all models.			
CRESTRON HARDWARE REQUIRED:	C2I-*ENET-*			
SETUP OF CRESTRON HARDWARE:	TCP/IP Port: 20060			
VENDOR FIRMWARE:	PKG2.261AA			
VENDOR SETUP:	Go to Home -> Network -> Home Network Setup -> IP Control Turn Simple IP Control on Tested with Authentication set to Normal			
CABLE DIAGRAM:	N/A			

CONTROL:				
Power_ <on off="" toggle=""></on>	D	Pulse to turn the power on and off.		
Volume_ <up down=""></up>	D	Press and hold to adjust the volume.		
Volume_Mute_ <on off="" toggle=""></on>	D	Pulse to turn the volume mute on and off.		
Input_*	D	Pulse to select the desired input.		
Picture_Mute_ <on off="" toggle=""></on>	D	Pulse to turn the picture mute on and off.		
PIP_ <on off="" toggle=""></on>	D	Pulse to turn the PIP on and off.		
Toggle_PIP_Position	D	Pulse to move the PIP location.		
IR_Emulation_*	D	Inputs to emulate the IR remote.		





Partner: Sony

Model: 2014 Bravia TV

Device Type: TV



TCP/IP_Connect-F	D	Digital signal to be routed from the Connect-F output of the TCP/IP Client symbol.
From_Device	S	Serial signal to be routed from the RX\$ output of the TCP/IP Client symbol.

FEEDBACK:		
Power_Is_ <on off=""></on>	D	High to indicate the current power state.
Volume_Level	Α	Analog signal to indicate the current volume level.
Volume_Mute_Is_ <on off=""></on>	D	High to indicate the current volume mute state.
Input_ls_*	D	High to indicate the currently selected input.
Picture_Mute_Is_ <on off=""></on>	D	High to indicate the current picture mute state.
PIP_Is_ <on off=""></on>	D	High to indicate the current PIP state.
Current_TV_Channel_Text	S	Serial signal indicating the currently tuned TV channel.
To_Device	S	Serial signal to be routed to the TX\$ input on the TCP/IP Client symbol.

TESTING:	
OPS USED FOR TESTING:	CP3: 1.010.0060
SIMPL WINDOWS USED FOR TESTING:	4.02.56
DEVICE DB USED FOR TESTING:	62.01.001.00
CRES DB USED FOR TESTING:	49.06.005.00
SYMBOL LIBRARY USED FOR TESTING:	922
SAMPLE PROGRAM:	Sony 2014 Bravia TV v1.0 Demo
REVISION HISTORY:	v1.0 – Original Release.