

Partner: Vitek
Model: OnCue
Device Type: Camera



GENERAL INFORMATION

SIMPLWINDOWS NAME:	Vitek OnCue IP v1.0
CATEGORY:	Security
VERSION:	V1.0
SUMMARY:	The module will control Vitek OnCue via TCP/IP.
GENERAL NOTES:	The module will control Vitek OnCue via TCP/IP. The module will provide basic remote controller functions.
CRESTRON HARDWARE REQUIRED:	3-Series processor
SETUP OF CRESTRON HARDWARE:	TCP/IP
VENDOR FIRMWARE:	Unknown
VENDOR SETUP:	Connect the Vitek OnCue system on the same network as the Crestron processor. The used port for Crestron control should be defined as the web Interface port + 1. For example: Web Interface port: 9080 => Used Crestron Port: 9081.
CABLE DIAGRAM:	Standard network cable.

Partner: Vitek
Model: OnCue
Device Type: Camera


CONTROL:

ID[1-4]	D	Pulse to select ID [1-4]
Key_Lock	D	Activates key lock mode.
Mute	D	Toggles the mute state.
Iris-	D	Pulse to decrease the iris value.
Iris+	D	Pulse to increase the iris value.
Menu/ESC	D	Calls and gets into the main menu. Returns to previous menu screen. Exits from various function and menu screens.
Enter	D	Pulse to press enter.
Up/Down/Left/Right	D	Pulse to press Up/Down/left/Right
Slow	D	Pulse to activate slow mode. In playback mode, max X1/120 slow forward playback speed is supported.
Fast	D	Pulse to activate fast mode. In playback mode, max X 120 forward playback speed is supported.
Search	D	Enters the search menu screen.
Copy	D	Pulse to select copy.
PTZ	D	Enters PTZ control mode.
RFAST	D	Pulse to activate reverse fast. Max X 120 reverse playback speed is supported.
Seq	D	Pulse to adjust the sequence in which the screens are displayed.
RSLOW	D	Pulse to activate reverse slow. Max X 1/120 reverse playback speed is supported.
Play	D	Pulse to select Play/Pause.
Freeze	D	Pulse to freeze the image.
Power	D	Pulse to toggle the power status.
MULTI	D	Pulse to show multiple channels.
Panic	D	Activates panic record mode

Partner: Vitek
Model: OnCue
Device Type: Camera



CH[1-16]	D	Pulse to select channel [1-16]
Function	D	Pulse to select the function list.
Four_Split	D	Pulse to select four split mode.
Nine_Split	D	Pulse to select nine split mode.
Sixteen_Split	D	Pulse to select sixteen split mode.

FEEDBACK:

Command_is_Processed	D	Pulses to acknowledge that a command was executed.
----------------------	---	--

PARAMETERS:

IP Address	S	The IP address of the OnCue system.
Port	A	The TCP port used for communication.
User Name	S	The user name for the DVR.
Password	S	The password for the DVR.

TESTING:

OPS USED FOR TESTING:	V1.011.0023
SIMPL WINDOWS USED FOR TESTING:	4.02.65
DEVICE DB USED FOR TESTING:	65.00.002.00
CRES DB USED FOR TESTING:	51.00.003.00
SYMBOL LIBRARY USED FOR TESTING:	941
SAMPLE PROGRAM:	Vitek OnCue IP v1.0 MC3 Demo
REVISION HISTORY:	v1.0 – Initial Release