

Partner: AVPro Edge  
Models: MXNet  
Device Type: AVPro Edge MXNet



## GENERAL INFORMATION

<b>SIMPLWINDOWS NAME:</b>	AVPro Edge MXNet DestinationRouter v1.2
<b>CATEGORY:</b>	AVPro Edge MXNet
<b>VERSION:</b>	1.2
<b>SUMMARY:</b>	<p>This module works in conjunction with the AVPro MXNet CommandProcessor v1.2 module and the AVPro MXNet Encoder/Decoder v1.2 modules to process routes between encoders and decoders. The full suite of AVPro MXNet modules includes:</p> <ul style="list-style-type: none"><li>• AVPro MXNet CommandProcessor v1.2</li><li>• AVPro MXNet Encoder v1.2</li><li>• AVPro MXNet Decoder v1.2</li><li>• AVPro MXNet SerialPort v1.2</li><li>• AVPro MXNet IRPort v1.2</li><li>• AVPro MXNet CEC v1.2</li><li>• AVPro MXNet DestinationRouter v1.2</li><li>• AVPro MXNet MultiDestinationRouter v1.2</li><li>• AVPro MXNet VW DecoderAssign v1.2</li><li>• AVPro MXNet VW Layout v1.2</li><li>• AVPro MXNet VW LayoutRecall v1.2</li></ul>
<b>GENERAL NOTES:</b>	<p>This module requires one instance of the AVPro MXNet CommandProcessor v1.2 module to register with, , a matching instance of the AVPro MXNet Encoder v1.2 for each encoder for source routing, and a matching instance of the AVPro MXNet Decoder v1.2 for the decoder to route to.</p>
<b>CRESTRON HARDWARE REQUIRED:</b>	4-Series processor, 3-Series processor
<b>SETUP OF CRESTRON HARDWARE:</b>	N/A
<b>VENDOR FIRMWARE:</b>	MXNet Control Box v2.28 MXNet Encoder v3.39 MXNet Decoder v4.21
<b>VENDOR SETUP:</b>	N/A

Partner: AVPro Edge  
Models: MXNet  
Device Type: AVPro Edge MXNet



## PARAMETERS:

<b>Command_Processor_ID</b>	The unique identifier of the command processor module that this module registers with.
<b>Matrix_Destination_Index</b>	<p>Specifies the unique index of the decoder this module is associated with.</p> <p>The AVPro MXNet Decoder v1.2 with each associated Destination_Index must be added to the program for the module to know which decoder in your system to route.</p>
<b>MultiRoute Group ID List</b>	<p>Specifies the group ID for this destination router. When assigned a MultiRoute Group ID, this destination router can receive route commands as part of a broadcast from the AVPro MXNet MultiDestinationRouter module. This destination router can be assigned multiple groups, each group ID should be specified in a comma-separated list.</p> <p>EX: 1,5,6</p>

Partner: AVPro Edge  
Models: MXNet  
Device Type: AVPro Edge MXNet



## CONTROL:

		Analog value specifies the encoder with the matching Matrix Source Index parameter.
<b>Source_Route</b>	A	To clear the route, use a 0 on this signal.  The AVPro MXNet Encoder v1.2 with each associated Source_Index must be added to the program for the module to know which encoder in your system to route.
<b>Take_Route</b>	D	Pulse to send the enabled route types from the encoder specified by the Source_Route analog input to the decoder specified by the Matrix Destination Index.
<b>Enable_Video</b>	D	Latch high to enable video routing from the source route specified by the <b>Source_Route</b> analog input.
<b>Enable_Audio</b>	D	Latch high to enable audio routing from the source route specified by the <b>Source_Route</b> analog input.
<b>Enable_USB</b>	D	Latch high to enable USB routing from the source route specified by the <b>Source_Route</b> analog input.
<b>Enable_Infrared</b>	D	Latch high to enable infrared routing from the source route specified by the <b>Source_Route</b> analog input.
<b>Enable_Serial</b>	D	Latch high to enable serial routing from the source route specified by the <b>Source_Route</b> analog input.

Partner: AVPro Edge  
Models: MXNet  
Device Type: AVPro Edge MXNet



## FEEDBACK:

<b>Is_Initialized</b>	D	Digital high indicates this module has been initialized with the command processor module.
<b>Source_Video_Fb</b>	A	Integer value indicates the routed video source to decoder with the matching Matrix Destination Index.
<b>Source_Audio_Fb</b>	A	Integer value indicates the routed audio source to decoder with the matching Matrix Destination Index.
<b>Source_USB_Fb</b>	A	Integer value indicates the routed USB source to decoder with the matching Matrix Destination Index.
<b>Source_Infrared_Fb</b>	A	Integer value indicates the routed infrared source to decoder with the matching Matrix Destination Index.
<b>Source_Serial_Fb</b>	A	Integer value indicates the routed serial source to decoder with the matching Matrix Destination Index.

Partner: AVPro Edge  
Models: MXNet  
Device Type: AVPro Edge MXNet

**TESTING:**

**OPS USED FOR TESTING:** VC4 v4.0000.00007  
CP4 v2.8000.00017  
CP3 v1.8001.5061.26823

**SIMPL WINDOWS USED FOR TESTING:** 4.2000.00

**CRES DB USED FOR TESTING:** 215.0000.003.00

**DEVICE DATABASE:** 200.23500.001.00

**SYMBOL LIBRARY USED FOR TESTING:** 1177

**SAMPLE PROGRAM:** AVPro Edge MXNet v1.2 Demo.smw

**REVISION HISTORY:**

- v1.0 – Initial Release
- v1.1 – Fixed SerialPort transmitted and received data.
  - Made updates to allow a Wallplate Encoder to initialize with this suite.
- v1.2 – Isolated serial communication queue to provide device control responsiveness.
  - Corrected unsolicited data parsing impacting hotplug detected and resolution.