

Manufacturer: Bose
Model: EX Series
Device Type: Digital Signal Processor



GENERAL INFORMATION

| | |
|------------------------------------|---|
| SIMPLWINDOWS NAME: | Bose EX Series Source Selector Control v3.0 |
| CATEGORY: | Conferencing |
| VERSION: | 3.0 |
| SUMMARY: | The Source Selector Control Component controls the routing of a source selector module. |
| CRESTRON HARDWARE REQUIRED: | Crestron 3-Series or 4-Series processor. |
| VENDOR FIRMWARE: | v2.520 |

Manufacturer: Bose
Model: EX Series
Device Type: Digital Signal Processor

**PARAMETERS:**

| | |
|-----------------------------|--|
| Module_Name | Set to the name of the source selector module that will be controlled. |
| Command_Processor_ID | The unique identifier for the command processor module this module will register with. |

Manufacturer: Bose
Model: EX Series
Device Type: Digital Signal Processor

**CONTROL:**

| | | |
|---------------------|---|---|
| Input_Select | A | Set to the input number that will be routed to the output of the source selector. |
| Enable | D | Latch high to enable this component. |

Manufacturer: Bose
Model: EX Series
Device Type: Digital Signal Processor

**FEEDBACK:**

| | | |
|-----------------------|---|---|
| Is_Initialized | D | Indicates the module is registered to the command processor and is synchronized with current device state when the signal is high, or not synchronized with current device state when the signal is low. |
| Current_Input | A | Displays the current input that is routed to the output of the source selector. |
| Is_Quarantined | D | Indicates that there was a problem getting this component initialized due to a configuration issue when the signal is high, or that no initialization issue occurred when the signal is low. A quarantined component will not prevent the command processor or other components from getting initialized. |

Manufacturer: Bose
Model: EX Series
Device Type: Digital Signal Processor

**TESTING:**

| | |
|---|---|
| OPS USED FOR TESTING: | CP3 1.8001.4788.20471 MC4 2.7000.00040 |
| SIMPL WINDOWS USED FOR TESTING: | 4.2000.00 |
| CRES DB USED FOR TESTING: | 212.0500.002.00 |
| DEVICE DATABASE: | 200.19000.002.00 |
| SYMBOL LIBRARY USED FOR TESTING: | 1168 |
| SAMPLE PROGRAM: | Bose EX Series v3.0 IP Demo.smw Bose EX Series v3.0 RS232 Demo.smw |
| REVISION HISTORY: | v3.0 – Initial Release |