

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**



## GENERAL INFORMATION

<b>SIMPLWINDOWS NAME:</b>	Lutron HomeWorks QSX LED Control v1.3.1
<b>CATEGORY:</b>	Lighting, HVAC, Shades
<b>VERSION:</b>	1.3.1
<b>SUMMARY:</b>	This module provides feedback monitoring capability for a LED component as part of a Lutron HomeWorks QSX solution.
<b>GENERAL NOTES:</b>	This module supports up to 50 LEDs. If more than 50 LEDs need to be managed, additional modules can be added to support the number of LEDs required. This module requires one instance of the Lutron HomeWorks QSX Command Processor module to register with.
<b>CRESTRON HARDWARE REQUIRED:</b>	Crestron 3-Series or 4-Series processor.
<b>SETUP OF CRESTRON HARDWARE:</b>	N/A
<b>VENDOR FIRMWARE:</b>	22.02.16f000
<b>VENDOR SETUP:</b>	Lutron HomeWorks QSX Processor

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**



## PARAMETER:

<b>Command_Processor_ID</b>	Setting indicates the identifier of the Command Processor module this module registers with. A single program can contain multiple LED modules where multiple Lutron processors are involved.
<b>LED_Href_ID[1]..LED_Href_ID[50]</b>	Setting indicates the reference identifier for the LED the corresponding analog signal will trigger. Example: for LED href: /led/811, enter the value 811 in the parameter field.

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**CONTROL:****LED\_Href\_ID[1] .. LED\_Href\_ID[50]****A**

Integer value indicates what the LED will be set to:

- 1 – LED On
- 2 – LED Off
- 3 – LED Normal Flash
- 4 – LED Rapid Flash
- 5 – Unknown

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**FEEDBACK:**

<b>Is_Initialized</b>	D	High indicates the module is initialized. The module is initialized when all component state information has been updated in the module to reflect current component state.
<b>LED_Href_ID[1]_Fb..LED_Href_ID[50]_Fb</b>	A	<p>Integer value indicates the current LED state:</p> <ul style="list-style-type: none"><li>1 – LED On</li><li>2 – LED Off</li><li>3 – LED Normal Flash</li><li>4 – LED Rapid Flash</li><li>5 – Unknown</li></ul>

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**



## TESTING:

**OPS USED FOR TESTING:** CP3 1.603.4242.34642  
CP4 2.8000.00017

**SIMPL WINDOWS USED FOR TESTING:** 4.22

**CRES DB USED FOR TESTING:** 217.05

**DEVICE DATABASE:** 200.260

**SYMBOL LIBRARY USED FOR TESTING:** 1184

**SAMPLE PROGRAM:** Lutron HomeWorks QSX v1.3.1 Demo IP.smw

**REVISION HISTORY:**

- v1.0 – Initial Release
- v1.1 – Added control inputs for LED control
- v1.2 – No changes have been made
- v1.3 – Corrected for errors when inputs are triggered before module is initialized