

Partner: Lutron
Model: MyRoom XC
Device Type: Lighting



GENERAL INFORMATION

SIMPLWINDOWS NAME:	Lutron MyRoom XC Shade Group Control v1.0
CATEGORY:	Lighting, HVAC, Shades
VERSION:	1.0
SUMMARY:	This module provides monitor and control capability for a Shade Group component as part of a Lutron MyRoom XC solution.
GENERAL NOTES:	This module interacts with a single Shade Group component, if multiple shade group components need to be managed, one module can be added for each component in the solution. This module requires one instance of the Lutron MyRoom XC Command Processor module to register with.
CRESTRON HARDWARE REQUIRED:	Crestron 4-Series processor
SETUP OF CRESTRON HARDWARE:	N/A
VENDOR FIRMWARE:	24.02.17f000
VENDOR SETUP:	Lutron MyRoom XC Processor

Partner: Lutron
Model: MyRoom XC
Device Type: Lighting

**PARAMETER:****Command_Processor_ID**

Setting indicates the identifier of the Command Processor module this module registers with. A single program can contain multiple shade modules where multiple Lutron processors are involved.

Zone_Href_ID

Setting indicates the reference identifier for the zone this shade control belongs to.
Example: for zone href: /Zone/1399, enter the value 1399 in the parameter field.

Partner: Lutron
Model: MyRoom XC
Device Type: Lighting

**CONTROL:**

Raise	D	Pulse to incrementally raise the shade position or latch high to continuously raise the shade position until the signal is latched low or the shade has reached its limit.
Lower	D	Pulse to incrementally lower the shade position or latch high to continuously lower the shade position until the signal is latched low or the shade has reached its limit.
Set_Level	D	Pulse to set the discrete value of the lift position specified by the Level analog input signal. <i>For slider operations, use a press join to drive this signal high. When this is high, the corresponding analog value will be sent automatically on change. Using a '1' on a 'set' signal is discouraged and will have negative effect.</i>
Level	A	Integer value specifies the lift position to set as a percentage. Range is 0 to 65535.

Partner: Lutron
Model: MyRoom XC
Device Type: Lighting



FEEDBACK:

Is_Initialized	D	High indicates the module is initialized. The module is initialized when all component state information has been updated in the module to reflect current component state.
Level_Fb	A	Integer value indicates the current lift position as a percentage from 0 to 65535.

Partner: Lutron
Model: MyRoom XC
Device Type: Lighting

**TESTING:**

OPS USED FOR TESTING:	CP4 2.8003.00056
SIMPL WINDOWS USED FOR TESTING:	4.30
CRES DB USED FOR TESTING:	225.05
DEVICE DATABASE:	200.350
SYMBOL LIBRARY USED FOR TESTING:	1205
SAMPLE PROGRAM:	Lutron MyRoom XC v1.0 Demo IP.smw
REVISION HISTORY:	v1.0 – Initial Release