

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**



## GENERAL INFORMATION

<b>SIMPLWINDOWS NAME:</b>	Lutron HomeWorks QSX Area Control v1.1
<b>CATEGORY:</b>	Lighting
<b>VERSION:</b>	1.1
<b>SUMMARY:</b>	This module provides monitor and control capability for a Area control component as part of a Lutron HomeWorks QSX solution.
<b>GENERAL NOTES:</b>	This module interacts with a single Area component, if multiple Area components need to be managed, one module can be added for each component in the solution. This module requires one instance of the Lutron HomeWorks QSX Command Processor module to register with.
<b>CRESTRON HARDWARE REQUIRED:</b>	Crestron 3-Series processor. Crestron 4-Series processor (Firmware Version 2.5000 or later).
<b>SETUP OF CRESTRON HARDWARE:</b>	Crestron CP3 Crestron MC4
<b>VENDOR FIRMWARE:</b>	21.7.0.817
<b>VENDOR SETUP:</b>	Lutron HomeWorks QSX Processor

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**PARAMETER:**

<b>Command_Processor_ID</b>	Setting indicates the identifier of the Command Processor module this module registers with. A single program can contain multiple zone modules where multiple Lutron processors are involved.
<b>Fade_Time</b>	Setting indicates the time interval in seconds for lighting to adjust to a new level. Range is 0 to 14400.
<b>Area_Href_ID</b>	Setting indicates the reference identifier for the Area this area control belongs to. Example: for area href: /Area/1399, enter the value 1399 in the parameter field.

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**CONTROL:**

<b>Set_DimLevel</b>	D	Pulse to set the discrete value of the brightness specified by the Dim_Level analog input signal. <i>For slider operations, use a press join to drive this signal high. When this is high, the corresponding analog value will be sent automatically on change. Using a '1' on a 'set' signal is discouraged and will have negative effect.</i>
<b>Dim_Level</b>	A	Integer value specifies the dim level to set as a percentage. Range is 0 to 65535.
<b>FadeTime</b>	A	Integer value specifies the fade time in seconds. Range is 0 to 14400.

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**FEEDBACK:**

<b>Is_Initialized</b>	D	High indicates the module is initialized. The module is initialized when all component state information has been updated in the module to reflect current component state.
<b>DimLevel_Fb</b>	A	Integer value indicates the current dim level as a percentage from 0 to 65535.
<b>FadeTime_Fb</b>	A	Integer value indicates the current fade time in seconds. Range is 0 to 14400.

**Partner: Lutron**  
**Model: HomeWorks QSX**  
**Device Type: Lighting**

**TESTING:**

<b>OPS USED FOR TESTING:</b>	CP3 1.8001.0075 MC4 2.7000.00031.01
<b>SIMPL WINDOWS USED FOR TESTING:</b>	4.17
<b>CRES DB USED FOR TESTING:</b>	206.0500.004.00
<b>DEVICE DATABASE:</b>	200.9500.001.00
<b>SYMBOL LIBRARY USED FOR TESTING:</b>	1144
<b>SAMPLE PROGRAM:</b>	Lutron HomeWorks QSX v1.1 Demo IP.smw
<b>REVISION HISTORY:</b>	v1.1 – Initial Release