

SIMPLWINDOWS NAME: Sharp LCD Projector Basic Controls

CATEGORY: Monitor

VERSION: 1.0

SUMMARY: Controls power/source selection/mode/volume

GENERAL NOTES: This module will control all the basic functions of a Sharp LCD projector. It was tested on both an XG-V10WU and an XG-P20XU.

CRESTRON HARDWARE REQUIRED: CNXCOM-2,
ST-COM

SETUP OF CRESTRON HARDWARE: Baud Rate - 9600
Parity - None
Data Bits - 8
Stop Bits - 1

VENDOR FIRMWARE: None

VENDOR SETUP: None

CABLE NUMBER: CNSP-532

CONTROL:

POWER-ON/OFF	D	Pulse to turn the screen on or off.
AUTO-POWER-OFF-*	D	Pulse to enable/disable the auto-power off feature.
PICTURE-MUTE-*	D	Pulse to turn the picture mute on/off.
INPUT-*	D	Pulse to select on of the sources.
PICTURE-*	D	Pulse to select one of the two available modes.
OSD-ON/OFF (LEVEL-A/B)	D	Pulse to activate/deactivate the on screen menu.
VOLUME-UP/DOWN	D	Press and hold to ramp the volume up or down.
VOLUME-MUTE-ON/OFF/TOGGLE	D	Pulse to mute/unmute the audio.

FEEDBACK:

VOLUME-BAR	A	Indicates the last volume level sent from the Crestron system to the screen. Should be routed to a bargraph on a touchpanel.
SHARP-TX\$	S	Serial signal to be routed to a 2 way RS232 port.

OPS USED FOR TESTING: 5.12.26x

COMPILER USED FOR TESTING: SimplWindows Version 1.52.01

SAMPLE PROGRAM: Sharp LCD Projector Demo Program

REVISION HISTORY: None