

SIMPLWINDOWS NAME: TOA DP-0204

CATEGORY: Mixer

VERSION: 1.0

SUMMARY: Presets Recall and Mute functions

GENERAL NOTES: This module will recall 1 through 16 Presets and Mute control Preset Recall and Mute functions.

Unit ID must be set for the module to operate (See Test Program).

CRESTRON HARDWARE: CNXCOM, ST-COM

SETUP OF CRESTRON HARDWARE: Baud Rate - 9600
Parity - None
Data Bits - 8
Stop Bits - 1

VENDOR FIRMWARE: Version 2

VENDOR SETUP: Accessed via TOA Software

CABLE NUMBER: CNSP-121

CONTROL:

UNIT-ID A Set Unit Address in Hex Example: Unit-0 = 00h

RECALL_PRESET-1-16 D Send command to Recall Preset 1-16

MUTE-ON/OFF_1-4 D Toggle Mute On or Off for Output 1-4

FEEDBACK:

RECALL_PRESET-1-16-FB D Indicates that preset 1-16 was last recalled

TOA-TX\$ S Serial data string to be routed to a 2-way RS232 port

OPS USED FOR TESTING: 3.18.06, 5.01.29x

COMPILER USED FOR TESTING: SimplWindows Version 1.20.04

SAMPLE PROGRAM: Test0204

REVISION HISTORY: None