



Manufacturer: World Wide Programming B.V.
Model: WWP Panel Extras v1.0
Device Type: Software module - WWP Home Config

CONTACT SUPPORT: (please fill out carefully)

COMPANY NAME:	World Wide Programming B.V.
SUPPORT CONTACT:	Leonel Geagea
EMAIL ADDRESS:	info@worldwideprogramming.nl
PHONE:	+31 6 1512 5959
ADDRESS:	Rotterdam, the Netherlands
NOTES:	Website: https://www.worldwideprogramming.nl . Support in English and Dutch; please include the processor model, firmware and the Status / License_Status text of WWP Core.

GENERAL INFORMATION

SIMPLWINDOWS NAME:	WWP Panel Extras v1.0
CATEGORY:	User Interface
VERSION:	1.0
SUMMARY:	Fireplace and garage door of the routed room, house scenes and All off, media player routing and Security visibility for one touch panel.
GENERAL NOTES:	One instance per touch panel. All WWP Panel modules of one panel share the same Panel_Number; the room that panel is routed to (WWP Panel Rooms) decides what this module shows. Signal names follow the WWP Panel UI contract (CH5), so the module can be wired straight to the panel smart object. Media_Player_Nr = MSOR player of the routed room (0 = none); use it to route the MSOR / media player signals to this panel. Security_Visible is high when security is enabled in the configuration and allowed on this panel; all other Security signals go straight from the panel to your security module. Smart object on the WWP Panel UI: Fireplace, GarageDoor, House, MediaPlayer, Security. Requirements: WWP Core (once per program) and the SIMPL# library WwpConfig.clz in the same folder as the program. All WWP modules communicate with each other inside the processor; no extra wiring between modules is needed. Start-up: the module does not send any commands to devices at boot. After the configuration is loaded it only publishes the current state (names, visibility, feedback) so panels and logic are correct straight away.



Manufacturer: World Wide Programming B.V.
 Model: WWP Panel Extras v1.0
 Device Type: Software module - WWP Home Config

	Licensing: part of the commercial WWP Home Config package (licenses S / M / L, 7-day trial per processor). See "WWP Home Config v1.0 Help.pdf" for the complete system description.
CRESTRON HARDWARE REQUIRED:	4-Series control system (developed and tested on RMC4). 3-Series is not supported.
SETUP OF CRESTRON HARDWARE:	4-Series control system. Copy WwpConfig.clz next to the .smw program, add WWP Core once, then add the WWP modules you need. Load the program, open the web configuration (http://<processor-ip>:8090/) and enter the rooms, devices and panels.
VENDOR FIRMWARE:	N/A - software module (no third-party device).
VENDOR SETUP:	In the web configuration: Rooms > Fireplace / Garage door / Media player, House scenes, Security and Panels.
CABLE DIAGRAM:	N/A - logic module, no device connection.

CONTROL:

<u>Signal/Function Name</u>	<u>D,S,A</u>	<u>Digital, Serial, Analog signal property - description</u>
Fire_On / Fire_Off	D	From Fireplace.On / Off.
Fire_DimUp / Fire_DimDn	D	From Fireplace.DimUp / DimDn (high while held).
Garage_Open / Garage_Close	D	From GarageDoor.Open / Close.
House_AllOff	D	From House.AllOff: everything off in all buildings.
Fire_Level	A	From Fireplace.Level.
House_Recall	A	From House.Recall: house scene 1-5.

FEEDBACK:

Fire_On_Fb	D	To Fireplace.On_Fb.
Fire_Visible	D	To Fireplace.Visible.



Manufacturer: World Wide Programming B.V.
Model: WWP Panel Extras v1.0
Device Type: Software module - WWP Home Config

Garage_Open_Fb / Garage_Closed_Fb	D	To GarageDoor.Open_Fb / Closed_Fb.
Garage_Visible	D	To GarageDoor.Visible.
MediaPlayer_Visible	D	To MediaPlayer.Visible.
Security_Visible	D	To Security.Visible.
Fire_Level_Fb	A	To Fireplace.Level_Fb.
House_Active_Fb	A	To House.Active_Fb: active house scene, 0 = none.
House_OutsideTemp_Fb	A	To House.OutsideTemp_Fb (from WWP Core Outside_Temp).
Media_Player_Nr	A	MSOR player number of the routed room, 0 = none.
MediaPlayer_Player_Name	S	To MediaPlayer.Player_Name.

PARAMETERS:

Panel_Number	A	Panel number in the WWP config (panels[].nr). Default 1. Use the same number on every WWP Panel module of one touch panel.
--------------	---	--

TESTING: (please fill out carefully)

OPS USED FOR TESTING:	RMC4 - firmware 2.8005.00031
SIMPL WINDOWS USED FOR TESTING:	4.3200.02.01
DEVICE DB USED FOR TESTING:	200.470.001.00
CRES DB USED FOR TESTING:	228.60.002.00

©2013 Crestron Electronics, Inc.
15 Volvo Drive · Rockleigh, NJ 07647
800.237.2041 / 201.767.3400

<http://application.market.com>

For more information please contact our Crestron Application Market team at applicationmarket@crestron.com. The information contained on this document is privileged and confidential and for use by Crestron Authorized Dealers, CSP Members, A+ Partners and Certified Integrated Partners only. Specifications subject to change without notice.



Manufacturer: World Wide Programming B.V.
Model: WWP Panel Extras v1.0
Device Type: Software module - WWP Home Config

SYMBOL LIBRARY USED FOR TESTING: 1244

SAMPLE PROGRAM: WWP Software-InterfaceDemo (touch panel: WWPInterfaceDemo_v1.ch5z,
contract WWPInterfaceDemo.chd)

REVISION HISTORY: v1.0 - initial release.